



GASOLINE POWER INVERTER GENERATOR

Product Features and Benefits:

Provide clean power where it is needed at the time when it matters most.

Axemen Power Inverter Generator is a powerful inverter generator that is great for emergency backup power and remote power applications. It is powered by a commercial **KOHLER®** CH440 Command Pro OHV engine and produces a max power of 8000 Watts and a rated of 6500 Watts.

This generator has onboard processor that monitors both voltage output to ensure clean power safe to use with sensitive electronics. The design also gives a lower fuel consumption and much longer engine life.


The AX8000i has the following features and benefits:

- ❖ Reliable and Efficient 14HP **KOHLER®** Command OHV Engine:
 - ❖ Electric start for easy starting and backup recoil starter with automatic decompression.
 - ❖ Quiet operation with oversized muffler, silencer, and intake.
 - ❖ Low-Oil Shutdown.
- ❖ Hour meter, large fuel tane for up to 12 hours of run time.
- ❖ Heavy duty, rolled tube steel construction.
- ❖ **KOHLER®** Engine EPA certified.
- ❖ 3 Year limited **KOHLER®** engine & 2 Year limited warranty.

Model	AX8000i
Engine Brand and Model	KOHLER® CH440 Command Pro
Engine HP and Displacement	14 HP 420 cc
Engine Starting Method	Keyed Electric Start w/ Recoil Backup
Engine Warranty	3 Year Engine 2 Year Alternator
Max AC Output	8000 Watts
Rated AC Output	6500 Watts
Voltages	120/240 Single Phase
Outlets	(1) 5-20 Duplex (1) NEMA L14-50 (1) L5-30R (1) L14-30R
Frequency	60 Hertz
Run Time (50% Load)	13 Hours
Tank Size	6.6 Gallons
Sound Rating (Decibels)	70 dB
Shipping Weight	198 lbs.
Dimensions (L x W x H)	32 x 27.5 x 27 in. 81 x 70 x 69 cm.




see manual for details



5-20 Duplex



L5-30R



NEMA L14-50



L14-30R

POWERED BY

KOHLER®